



PCT/IB 0.4 / 0.4.4.2.0.

(08.03.05)

INVESTOR IN PEOPLE

REC'D 08 MAR 2005

WIPO PCT RO/IB

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ


PCT/IB04/04420

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.



Signed

Stephen Hordley

Dated

15 November 2004

**PRIORITY
DOCUMENT**

SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)


Patents Form 1/77

Patents Act 1977

Request for grant of a patent
 (the notes on the back of this form. You can also get
 an explanatory leaflet from the Patent Office to help
 fill in this form)



PCT/EP2004/013867



The Patent Office

Cardiff Road
 Newport
 Gwent NP9 1RH

Your reference

SC13039EI/CJH/GBRI/jt/KUTZ

Patent application number
 (The Patent Office will fill in this part)

05 DEC 2003

0328322.3

Full name, address and postcode of the or of
 each applicant (underline all surnames)

MOTOROLA, INC
 1303 EAST ALGONQUIN ROAD,
 SCHAUMBURG, ILLINOIS 60196,
 U.S.A.

00615336004
 Patents ADP number (if you know it)

08281107001

If the applicant is a corporate body, give the
 country/state of its incorporation

U.S.A.

DELAWARE

Title of the invention **A DECODER FOR A WIRELESS COMMUNICATION DEVICE**

Name of your agent (if you have one)

CHRISTOPHER HARRISON

"Address for service" in the United Kingdom
 to which all correspondence should be sent
 (including the postcode)

EUROPEAN INTELLECTUAL PROPERTY DEPARTMENT
 MIDPOINT
 ALENCON LINK
 BASINGSTOKE
 HAMPSHIRE RG21 7PL
 UK
 ADP NO. 00001180006

Patents ADP number (if you know it)

07957749001

If you are declaring priority from one or more
 earlier patent applications, give the country
 and the date of filing of the or of each of these
 earlier applications and (if you know it) the or
 each application number

Country

Priority application number
 (if you know it)

Date of filing
 (day / month / year)

If this application is divided or otherwise
 derived from an earlier UK application,
 give the number and the filing date of
 the earlier application

Number of earlier application

Date of filing
 (day / month / year)

Is a statement of inventorship and of right
 to grant of a patent required in support of
 this request? (Answer 'Yes' if:

☒ YES ☐ NO

- a) any applicant named in part 3 is not an inventor, or
 - b) there is an inventor who is not named as an applicant, or
 - c) any named applicant is a corporate body.
- See note (d))

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form

Description 10 /

Claim(s) 3 /

Abstract 1 /

Drawing(s) 1 xl

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translations of priority documents

Statement of inventorship and right to grant of a patent (Patents Form 7/77) 3 /

Request for preliminary examination and search (Patents Form 9/77) 1 /

Request for substantive examination (Patents Form 10/77) 1 /

Any other documents 1 x FEE SHEET
(please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date

12/1/2003

12. Name and daytime telephone number of person to contact in the United Kingdom

CHRISTOPHER HARRISON

Eliza LAURIE

01256-790763

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

DUPLICATE

A DECODER FOR A WIRELESS COMMUNICATION DEVICE

The present invention relates to a decoder for a wireless communication device.

10 Wireless communication systems are widely deployed to provide various types of communications such as voice and data. One such system is wideband code division multiple access WCDMA, which has been adopted in various competing wireless communication standards, for example 3rd generation partnership project 3GPP and 3GPP2.

15 To overcome data corruption that can occur during RF transmission the different wireless communication standards typically include some form of channel coding, where one common channel coding technique is turbo coding.

20 Turbo coding involves the use of a turbo encoder for encoding a code segment (i.e. a data packet) and a turbo decoder for the decoding of the encoded code segment.

25 A turbo encoder includes two convolutional encoders and an interleaver, where the interleaver shuffles (i.e. interleaves) the information bits in the packet in accordance with a specified interleaving scheme.

30 The turbo encoder uses a first convolutional encoder to encode information bits within a packet to generate a first sequence of parity bits in parallel to the interleaver shuffling the information bits, where the shuffled information bits are encoded by a second encoder to generate a second sequence of parity bits. The information bits and the parity bits in the first and second sequence are then modulated and transmitted to a receiver.

5

The information bits and the first and second sequence of parity bits are received by a receiver and decoded by a turbo decoder.

10 The turbo decoder initially stores the received information bits and the parity bits in the first and second sequence in a buffer. Initially, the information bits and the first sequence of parity bits from the first convolutional encoder are retrieved from the buffer and decoded by a first soft input soft output SISO decoder to provide 'extrinsic' information indicative of adjustments in the confidence in the detected values for the information bits. Intermediate results that include the
15 extrinsic information from the first SISO decoder are then stored in the buffer in an interleaved order matching the code interleaving used at the transmitter.

The intermediate results, the information bits and the second sequence of parity bits from the second encoder are retrieved from the buffer and decoded by a
20 second SISO decoder to provide extrinsic information indicative of further adjustments in the confidence in the detected values for the information bits. Intermediate results that comprise the extrinsic information from the second SISO decoder are then stored in the buffer in a deinterleaved order complementary to the code interleaving performed at the transmitter. The intermediate results are
25 used in a next decoding iteration performed by the turbo decoder. The turbo decoder performs a predetermined number of decoding iterations before producing a decision on the value of the decoded information bit.

Commonly used algorithms used within SISO decoders are the maximum a
30 posteriori MAP decoding algorithm and the log MAP decoding algorithm. The log MAP decoding algorithm is analogous to the MAP decoding algorithm but performed in the logarithmic domain.

5

The MAP decoding algorithm uses forward state metrics, commonly referred to as alphas α , and backward state metrics, commonly referred to as betas β , to determine soft output results, where the forward state metrics α and backward state metrics β characterise a state in a trellis structure.

10

The MAX^* function is used within the log-MAP algorithm and is represented by $\text{MAX}^*(a(n), b(n))$, where $a(n)$ and $b(n)$ are inputs to the MAX^* function. The inputs $a(n)$ and $b(n)$ can be forward state metrics, backward state metrics or a combination of both.

15

The $\text{MAX}^*(a(n), b(n))$ function is equal to $\text{MAX}(a(n), b(n))$ plus a correction value where the correction value is equal to $\log(1 + \exp(-|a(n) - b(n)|))$.

20

The $\text{MAX}(a(n), b(n))$ term of the equation is usually straight forward to calculate, however the correction value is relatively complicated to calculate and is usually approximated using either a linear approximation, a step approximation or a look-up table.

25

As the state metric calculations are performed within the SISO decoder the values within the accumulated path metrics can overflow leading to incorrect results.

30

One solution to the overflow problem involves the use of modulo arithmetic's. A modulo n operation on a number provides the remainder when the number is divided by n , for example $10(\text{binary } 1010) \bmod 8 = 2(\text{binary } 010)$ and $28(\text{binary } 11100) \bmod 16 = 12(\text{binary } 1100)$. Consequently, as can be seen from the examples, determine a value for a modulo operation where the remainder is a value to the power of two is simply a question of masking off any unwanted bits.

- 5 The modulo function, as illustrated in figure 1, can be regarded as a sawtooth function.

An alternative implementation of the modulo function can be defined by:
$$x \bmod F = x - 2F \left\lfloor \frac{x+F}{2F} \right\rfloor$$
, which allows negative numbers to be accommodated.

- 10 This function is illustrated in figure 2.

It is desirable to have an apparatus and method for generating a linearly approximated MAX* log MAP algorithm that operates on modulo functions.

- 15 In accordance with a first aspect of the present invention there is provided a decoder for a wireless communication device according to claim 1.

In accordance with a second aspect of the present invention there is provided a method for generating a MAX* value according to claim 8.

20

An embodiment of the invention will now be described, by way of example, with reference to the drawings, of which:

Figure 1 illustrates a graphical representation of a first modulo function;

25

Figure 2 illustrates a graphical representation of a second modulo function;

Figure 3 illustrates a graphical representation of the variation in the MAX* correction term versus $|a(n) - b(n)|$;

30

5 Figure 4 illustrates a decoder according to an embodiment of the present invention.

The curve A in figure 3 illustrates the correction term for the $\text{MAX}^*(a(n), b(n))$ function (i.e. $\text{MAX}^*(a(n), b(n)) - \text{MAX}(a(n), b(n))$) as a function of $|a(n) - b(n)|$, where
 10 $|a(n) - b(n)|$ is the absolute value of the difference between $a(n)$ and $b(n)$.

As can be seen from curve A the correction term is greatest for low values of $|a(n) - b(n)|$ and gradually decreases to zero as $|a(n) - b(n)|$ increases.

15 As stated above, an easy technique for approximating the correction term is the use of linear approximation, as illustrated by line B in figure 3. As illustrated, the linear approximation provides a close approximation for the correction term for low values of $|a(n) - b(n)|$. The intersection of the line B on the $|a(n) - b(n)|$ axis indicates the $|a(n) - b(n)|$ value above which the linear approximation correction
 . 20 term goes to zero. Consequently, using linear approximation, the intersection point determines a threshold value, designated C, for determining if a correction value is to be applied to $|a(n) - b(n)|$, where the intersection point is defined by the linear approximation equation.

25 The use of the linear approximation technique allows easy calculation of the MAX^* function, as described below.

One suitable linear approximation equation (i.e. the correction term used) is given by $\text{MAX}(0, (C - |a(n) - b(n)|) / 2)$.

30

Consequently, the MAX^* function can be written as:

5

$$\text{MAX}(a(n), b(n)) + \text{MAX}\left(0, \frac{(C - |a(n) - b(n)|)}{2}\right)$$

$$= \text{MAX}(0 + \text{MAX}(a(n), b(n)), \frac{(C - |a(n) - b(n)|)}{2} + \text{MAX}(a(n), b(n)))$$

$$= \text{MAX}(a(n), b(n), \frac{(C - |a(n) - b(n)|)}{2} + \text{MAX}(a(n), b(n)))$$

10

$$= \text{MAX}(a(n), b(n), \frac{(a(n) + b(n) + C)}{2})$$

To minimise the problem of accumulated state metric overflow, as discussed above, the above terms are converted into their corresponding 'modF' values where F is selected such that $|a(n) - b(n)| < F$. F is chosen by analysing the algorithm and determining what would be the maximum possible value of $|a(n) - b(n)|$ for any a(n) and b(n) that can enter the MAX* function.

To ease the hardware implementation for handling the modulo value F is preferable a value to the power of two.

The modF of a(n) becomes $a(n) \bmod F$.

The modF of b(n) becomes $b(n) \bmod F$.

25

However, the modF of $(a(n) + b(n) + C)/2$ is

$$\left(a(n) \bmod F + \frac{(b(n) \bmod F - a(n) \bmod F) \bmod F + C}{2} \right) \bmod F$$

5 and not $\left(\frac{a(n) \bmod F + b(n) \bmod F + C}{2} \right) \bmod F$.

This is demonstrated by the following:

The equation $x \bmod F$ is equivalent to $x - 2F \left\lfloor \frac{x+F}{2F} \right\rfloor$, where the $\lfloor x \rfloor$ term is

10 the floor of 'x'.

Accordingly:

$$(a(n)+C) \bmod F = (a(n) \bmod F + C) \bmod F$$

15 and

$$(a(n)-b(n)) \bmod F = a(n) - b(n) \text{ if and only if } |a(n) - b(n)| < F$$

Using these two identities proves:

$$20 \quad \left(\frac{a(n) + b(n) + C}{2} \right) \bmod F = \left(a(n) + \left(\frac{b(n) - a(n) + C}{2} \right) \right) \bmod F$$

$$= \left(a(n) \bmod F + \left(\frac{(b(n) - a(n)) \bmod F + C}{2} \right) \right) \bmod F$$

$$= \left(a(n) \bmod F + \frac{((b(n) \bmod F - a(n) \bmod F) \bmod F + C)}{2} \right) \bmod F.$$

25

5. For values of $C < F/2$ an alternative implementation of the modulo of a linear approximation of a MAX function is equal to:

$$\left(\left(\frac{(a(n) \bmod F + C) \bmod F + b(n) \bmod F}{2} \right) \bmod F + F * s \right) \bmod F$$

10 where s is calculated from the binary expression $s = [a(m) \text{ xor } b(m)]$ and $[(a(m) \text{ xor } a(m-1)) \text{ and } ((b(m) \text{ xor } b(m-1))]$, where a and b are represented by m bits so that $a(m)$ is the most significant bit of a and $a(m-1)$ is next to the most significant bit.

15 This algorithm is easy to calculate in silicon as s involves only binary operations and F is chosen to be a power of two.

A decoder 400 for implementing the above MAX* equation is shown in figure 4 and is arranged to output $\text{MAX}(a(n) \bmod F, b(n) \bmod F)$ when $|a(n) - b(n)|$ is greater than the threshold value C and to output

20 $\left(a(n) \bmod F + \frac{((b(n) \bmod F - a(n) \bmod F) \bmod F + C)}{2} \right) \bmod F$ when $|a(n) - b(n)|$ is less than the threshold value C . If $|a(n) - b(n)|$ equals C then either $\text{MAX}(a(n) \bmod F, b(n) \bmod F)$ or

$$\left(a(n) \bmod F + \frac{((b(n) \bmod F - a(n) \bmod F) \bmod F + C)}{2} \right) \bmod F \text{ can be output.}$$

25 The decoder 400 includes a first subtracting unit 401, a second subtracting unit 402, a calculator 403 in the form of an adder unit and a selector 404 in the form of a multiplexer unit. The first subtracting unit 401, the

5 second subtracting unit 402 and the adder unit 403 are each arranged to receive $a(n) \bmod F$, $b(n) \bmod F$ and the threshold value C .

10 The first subtracting unit 401 is arranged to generate the sign of $(b(n) \bmod F - a(n) \bmod F - C) \bmod F$. The second subtracting unit 402 is arranged to generate the sign of $(a(n) \bmod F - b(n) \bmod F - C) \bmod F$. The adder unit 403 is arranged to generate $\left(a(n) \bmod F + \frac{((b(n) \bmod F - a(n) \bmod F) \bmod F + C)}{2} \right) \bmod F$, where the division by two corresponds to a shift in bit position by one.

15 The $\bmod F$ operation is performed by ignoring the overflow (i.e. the carry bit of the msb bit addition is ignored).

The output from the first subtracting unit 401, the second subtracting unit 402 and the adding unit 403 (i.e. the sign of $(b(n) \bmod F - a(n) \bmod F - C) \bmod F$, the sign of $(a(n) \bmod F - b(n) \bmod F - C) \bmod F$ and

20 $\left(a(n) \bmod F + \frac{((b(n) \bmod F - a(n) \bmod F) \bmod F + C)}{2} \right) \bmod F$ respectively) are provided to the multiplex unit 404 along with the values of $a(n) \bmod F$ and $b(n) \bmod F$.

25 The multiplexer 404 is arranged to output a $\text{MAX}^*(a(n) \bmod F, b(n) \bmod F)$ equal to $a(n) \bmod F$ when the sign of $(a(n) \bmod F - b(n) \bmod F - C) \bmod F$ is positive and the sign of $(b(n) \bmod F - a(n) \bmod F - C) \bmod F$ is negative.

5


The multiplexer 404 is arranged to output a $\text{MAX}^*(a(n) \bmod F, b(n) \bmod F)$ equal to $b(n) \bmod F$ when the sign of $(a(n) \bmod F - b(n) \bmod F - C) \bmod F$ is negative and the sign of $(b(n) \bmod F - a(n) \bmod F - C) \bmod F$ is positive.

10

The multiplexer 404 is arranged to output a $\text{MAX}^*(a(n) \bmod F, b(n) \bmod F)$ equal to $\left(a(n) \bmod F + \frac{((b(n) \bmod F - a(n) \bmod F) \bmod F + C)}{2} \right) \bmod F$ when the sign of $(a(n) \bmod F - b(n) \bmod F - C) \bmod F$ is negative and the sign of $(b(n) \bmod F - a(n) \bmod F - C) \bmod F$ is negative.

15

It will be apparent to those skilled in the art that the disclosed subject matter may be modified in numerous ways and may assume many embodiments other than the preferred forms specifically set out as described above, for example the above embodiments could be arranged such that the modulo for other linear approximation equations can be calculated and an additional subtracting unit could be used to determine the sign of $a(n) - b(n)$ to assist the selection process.



CLAIMS

1. A decoder for a wireless communication device comprising a calculator for calculating the modulo of a linear approximation of a MAX* function; and a selector for selecting a MAX* output value from the group $a(n) \bmod F$, $b(n) \bmod F$, and the calculated modulo based upon a determination as to whether a predetermined threshold value for $|a(n) - b(n)|$ has been met, where $a(n)$ is a first state metric, $b(n)$ is a second state metric, C is the predetermined threshold value and F is a value greater than $|a(n) - b(n)|$.
2. A decoder according to claim 1, wherein the calculator is arranged to calculate the modulo of a linear approximation of a MAX function using:
- $$\left(a(n) \bmod F + \frac{((b(n) \bmod F - a(n) \bmod F) \bmod F + C)}{2} \right) \bmod F.$$
3. A decoder according to claim 1, wherein the calculator is arranged to calculate the modulo of a linear approximation of a MAX function using:
- $$\left(\left(\frac{(a(n) \bmod F + C) \bmod F + b(n) \bmod F}{2} \right) \bmod F + F * s \right) \bmod F, \text{ where } s \text{ is equal to } [a(m) \text{ xor } b(m)] \text{ and } [(a(m) \text{ xor } a(m-1)) \text{ and } ((b(m) \text{ xor } b(m-1))$$
4. A decoder according to claim any preceding claim, wherein the determination is based upon the sign of $(a(n) \bmod F - b(n) \bmod F - C) \bmod F$ and the sign of $(b(n) \bmod F - a(n) \bmod F - C) \bmod F$.

5. A decoder according to any preceding claim, wherein the selector is arranged to select and output the modular of the linear approximation of a MAX*function if the value $|a(n) - b(n)|$ is less than the predetermined threshold value.
- 10 6. A decoder according to any preceding claim, wherein the value of F is to the power of two.
7. A decoder according to any preceding claim, wherein the selector is a multiplexer.
- 15 8. A decoder according to any preceding claim, wherein the calculator is an add module that is arranged to receive $a(n) \bmod F$, $b(n) \bmod F$ and C.
- 20 9. A method for generating a MAX* value, the method comprising receiving a first modulo state metric $a(n) \bmod F$, a second modulo state metric $b(n) \bmod F$ and a predetermined threshold value for $|a(n) - b(n)|$; calculating the modulo of a linear approximation of a MAX* function; and selecting a value from the group $a(n) \bmod F$, $b(n) \bmod F$, and the calculated modulo based upon a determination as to whether a predetermined threshold value for $|a(n) - b(n)|$ has been met.
- 25 10. A method according to claim 9, wherein the modulo of the linear approximation of a MAX function is calculated using:
- $$\left(a(n) \bmod F + \frac{((b(n) \bmod F - a(n) \bmod F) \bmod F + C)}{2} \right) \bmod F.$$

5

A method according to claim 9, wherein the modulo of the linear approximation of a MAX function is calculated using:

$$\left(\left(\frac{(a(n) \bmod F + C) \bmod F + b(n) \bmod F}{2} \right) \bmod F + F * s \right) \bmod F$$
, where s is equal to $[a(m) \text{ xor } b(m)]$ and $[(a(m) \text{ xor } a(m-1)) \text{ and } ((b(m) \text{ xor } b(m-1))]$.

10

11.A decoder substantially as hereinbefore described with reference to the figures.

12.A method substantially as hereinbefore described with reference to the figures.

15

5 ABSTRACT

A DECODER FOR A WIRELESS COMMUNICATION DEVICE

10 A decoder for a wireless communication device comprising a calculator for
calculating the modulo of a linear approximation of a MAX* function; and a selector
for selecting a MAX* output value from the group $a(n) \bmod F$, $b(n) \bmod F$, and the
calculated modulo based upon a determination as to whether a predetermined
threshold value for $|a(n) - b(n)|$ has been met, where $a(n)$ is a first state metric,
15 $b(n)$ is a second state metric, C is the predetermined threshold value and F is a
value greater than $|a(n) - b(n)|$.

(Figure 4)

20

1/1

$a \bmod 2F$




FIG. 1

$a \bmod F$




FIG. 2





FIG. 3

FIG. 4

400



**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record.**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☒ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☒ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☒ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.